

DRIVDONSTABELL KONSTANTSTRÖM

		350mA					350mA Dimbar		700mA					700mA Dimbar		Universal dimbar				
		PLR 74 520 81 DPL 74 520 82	KONVERTER 350 52 801 90	LVP 74 520 86	DCC 79 806 90	LED KONVERTER IP68 74 526 61	PLD 350 74 525 27	JOLLY MICRO 74 526 63	PLR 74 525 34	DCC 79 806 91	PD 74 520 99		LVO 74 525 39	PLD 700 74 525 28	JOLLY MD 74 526 66	JOLLY PRO 74 525 19	JOLLY HV 74 526 64	JOLLY MAXI / DALI US 79 806 51 79 806 52	JOLLY DIN 79 805 50	JOLLY MINI 79 804 74
350mA	Single Eye Multi	1-3st	1-2st	1/1-2st	1-4st	1-3st	1-4st	1st	-	-	-		-	-	1-4st	1-4st	1-5st	1-7st	1-5st	1-4st
	Single Eye Multi Square I	1-3st	1-2st	1/1-2st	1-4st	1-3st	1-4st	1st	-	-	-		-	-	1-4st	1-4st	1-5st	1-7st	1-5st	1-4st
	Single Eye Multi Square II	1st	1st	0/1st	1-2st	1st	1-2st	-	-	-	-		-	-	1-2st	1-2st	1-2st	1-3st	1-2st	1-2st
	Cone LED 1,2W	1-9st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1-12st	1-12st	1-16st	1-20 st	1-15 st	1-12st
	Bright Eye Multi 3 / IP54	1-3st	1-2st	1/1-2st	1-4st	1-3st	1-4st	1st	-	-	-		-	-	1-4st	1-4st	1-5st	1-7st	1-5st	1-4st
	Core 15°, 45°, 120°	1-9st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1-12st	1-12st	1-16st	1-20st	1-15 st	1-12st
	1202, 1206, 1208, 1210, 1218 Multi	1-3st	1-2st	1/2st	1-4st	1-3st	1-4st	1st	-	-	-		-	-	1-4st	1-4st	1-5st	1-6st	1-5 st	1-4 st
	LED-Spot Dot 45° / 140°	1-9st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1- 12st	1- 12st	1-16st	1-20st	1-15 st	1- 12 st
	Spot Mini 120°	1-9st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1- 12st	1- 12st	1-16st	1-20st	1-15st	1- 12st
	Dot VP IP44 / Spot Mini VP IP44	1-9st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1- 12st	1- 12st	1-16st	1-20st	1-15st	1- 12st
	Window I / II 1,2w	1-9st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1-12st	1-12st	1-16st	1-20st	1-15st	1-12st
	Spot It Micro	1-9st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1-12st	1-12st	1-16st	1-20st	1-15st	1-12st
	Deco I, II, IV	1-9 st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1-12st	1-12st	1-16st	1-20st	1-15st	1-12st
	Decklight Super	1-9 st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1-12st	1-12st	1-16st	1-20st	1-15st	1-12st
	Spot Nauto 3X1W	1-3 st	1-2st	1/2st	1-4st	1-3st	1-4st	1st	-	-	-		-	-	1-4st	1-4st	1-5st	1-6st	1-5st	1-4st
	Spot Floor	1-9st	1-6st	1-3/1-6st	1-12st	1-9st	3-12st	1-4st	-	-	-		-	-	1-12st	1-12st	1-16st	1-20st	1-15st	1-12st
	LED Link	0,3-0,8m	0,3-0,6m	0,3/0,6m	-	0,3-0,8m	0,3-1m	0,3m	-	-	-		-	-	0,3-1m	0,3-1m	0,3-1,4m	0,3-1,8m	0,3-1,4m	0,3-1m
	Heatline 100	1st	-	-	1st	1st	1st	-	-	-	-		-	-	1st	1st	1st	2st	1st	1st
	Heatline 50	1st	1st	0/1st	1-2st	1-2st	1-2st	1st	-	-	-		-	-	1-3st	1-2st	1-3st	1-4st	1-3st	1-2st
	Nova Multi 7 / Tilt / Step	1st	1st	-	1-2st	1st	1-2st	-	-	-	-		-	-	2st	2st	2st	3st	2st	1-2st
500mA	2218 Multi	-	-	-	-	-	-	-	-	-	-		-	-	1-5st	1-4st	1-5st	1-7st	1-5st	1-4st
700mA	Alu Box I Multi 6	-	-	-	-	-	-	-	1st	1st	1-3st		1/1-2st	1-2st	1-4st	1-3st	-	1-7st	1-4st	1-2 st
	Alu Box II Multi 6	-	-	-	-	-	-	-	-	-	1st		0/1st	1st	1-2st	1st	-	1-3st	1-2st	1st
	Alu Box III Multi 6	-	-	-	-	-	-	-	-	-	1st		-	-	1st	1st	-	1-2st	1st	-
	Alu Square I Multi 6	-	-	-	-	-	-	-	1st	1st	1-3st		1/1-2st	1-2st	1-4st	1-3st	-	1-7st	1-4st	1-2st
	Alu Square II Multi 6	-	-	-	-	-	-	-	-	-	1st		0/1st	1st	1-2st	1st	-	1-3st	1-2st	1st
	Alu Square III Multi 6	-	-	-	-	-	-	-	-	-	1st		-	-	1st	1st	-	1-2st	1st	-
	Bend Multi 6	-	-	-	-	-	-	-	1st	1st	1-3st		1/1-2st	1-2st	1-4st	1-3st	-	1-7st	1-4st	1-2st
	Focus Twist Multi 6	-	-	-	-	-	-	-	1st	1st	1-3st		1/1-2st	1-2st	1-4st	1-3st	-	1-7st	1-4st	1-2st
	Spot Mini IP44	-	-	-	-	-	-	-	1-3st	1-4st	3-9st		1-3/5st	2-6st	1-12st	1-10st	-	1-20st	1-12st	1-8st
	Cone LED 3W	-	-	-	-	-	-	-	1-3st	1-4st	3-9st		1-3/6st	2-6 st	1-11st	1-9st	-	1-18st	1-11st	1-6st
	Bright Eye Multi 6 / Tilt / IP54 / 60°	-	-	-	-	-	-	-	1st	1st	1-3st		1/1-2st	1-2st	1-4st	1-3st	-	1-7st	1-4st	1-2st
	Bright Eye Multi 13 / Tilt	-	-	-	-	-	-	-	-	-	1st		0/1st	1st	1-2st	1st	-	1-3st	1-2st	1st
	Thin LED	-	-	-	-	-	-	-	1-3st	1-4st	3-9st		1-3/5st	2-6st	1-12st	1-10st	-	1-20st	1-12st	1-8st
	Window I 3W	-	-	-	-	-	-	-	1-3st	1-4st	3-9st		1-3/6st	2-6st	1-11st	1-9st	-	1-18st	1-11st	1-6st

Obs! Samtliga installationer ska följa våra rekommendationer av ledningslängder.

DRIVDONSTABELL KONSTANTSPÄNNING

		Jolly Universal				12V							24V							LED Dimmer Singelfärg		LED Trafo/Dimmer Singelfärg				LED Dimmer Singelfärg Teleco		LED Dimmer RGB		LED Dimmer RGB Teleco	
		JOLLY MD 74 526 66	JOLLY PRO 74 525 19	JOLLY HV 74 526 64	JOLLY MINI 79 804 74	PMR 8.4W 74 525 44	SLT 15W 74 520 88 52 812 91	SLT 20W 52 812 96	SLT 30W 52 812 52 52 812 92	SLT 60W 52 812 98	VST 12V 70W 79 805 60	ST2 12V 70W 79 805 61	LED TRAFO IP68.16W 52 805 66	PMR 8.4W 74 525 45		SLT 15W 74 520 87	SLT 30W 52 812 53	SLT 75W 52 812 99	VST 24V 70W 79 805 62	VST 24V 150W 79 805 64	ST2 24V 70W 79 805 63	ST2 24V 150W 79 805 65	KZO 12V/24V 75 504 75	LED DIMMER 12V/24V 79 851 64 79 851 65	MDR 12V 45W 79 844 42	MDR 24V 60W 79 844 43	VSTR 24V 120W 79 805 66	DIMMER SINGELFÄRG 79 851 72	LED DIMMER RGB/IR 79 851 60 79 851 61	DIMMER RGB 79 851 70 79 851 74	
12V DC	Slim	1-4st	1-4st	1-3st	1-4st	1-3st	1-7st	1-9st	1-13st	1-27st	1-33st	1-33st	1-7st	-	-	-	-	-	-	-	-	-	1-12 st	1-50 st	5-20 st	-	-	1-25x3 st	-	-	
	Point Round	2-16st	2-16st	2-14st	2-16st	2-14st	3-24st	4-30st	-	-	-	-	2-30st	-		-	-	-	-	-	-	-	1-48 st	1-200 st	20-80 st	-	-	1-100x3 st	-	-	
	Point Square	2-16st	2-16st	2-14st	2-16st	2-14st	3-24st	4-30st	-	-	-	-	2-30st	-		-	-	-	-	-	-	-	1-48 st	1-200 st	20-80 st	-	-	1-100x3 st	-	-	
	Stair Light	5-28st	5-28st	3-23st	5-28st	3-25st	3-40st	5-50st	5-80st	-	-	-	4-45st	-		-	-	-	-	-	-	-	1-80 st	1-333 st	34-150 st	-	-	1-166x3 st	-	-	
	LED Mini Disc	2-16st	2-16st	2-14st	2-16st	2-14st	2-24st	4-30st	-	-	-	-	2-30st	-		-	-	-	-	-	-	-	1-48 st	1-200 st	20-80 st	-	-	1-100x3 st	-	-	
	LEDstrip R 4.8W/M	0,05-1.5m	0,05-1.5m	0,05-1.5m	0,05-1.5m	0,05-1.5m	0,05-3m	0,05-4m	0,05-6m	0,05-12m	0,05-14m	0,05-14m	0,3-3m	-		-	-	-	-	-	-	-	0,05-5 m	0,05-20 m	2,5-9 m	-	-	0,05-10 m x3 st	-	-	
	LEDstrip R RGB 6,5W/M	0,1-1m	0,1-1m	0,1-1m	0,1-1m	0,1-1m	0,1-2m	0,1-2,5m	0,1-4,5m	0,1-9m	0,1-10m	0,1-10m	0,1-2m	-		-	-	-	-	-	-	-	-	-	-	-	-	-	0,1-11 m	0,1-7,5m x3 st	
	Duralight Led 12V	0,5-3m	0,5-3m	0,5-3m	0,5-3m	0,5-3m	0,6-5m	0,6-7m	0,6-10m	1-20m	1-25m	1-25m	0,5-5m	-		-	-	-	-	-	-	-	0,5-9m	0,5-40m	4-17m	-	-	0,5-20 m x3st	-	-	
24V DC	LED-ljuskälla G4	1-5st	1-5st	1-5st	1-5st	1-5st	1-9 st	1-12st	1-18st	-	-	-	1-9st	-		-	-	-	-	-	-	-	1-15st	1-62st	7-28st	-	-	1-31x3st	-	-	
	LED Extend 30	1-9st	1-9st	1-8st	1-9st	-	-	-	-	-	-	-	-	1-3st		1-7st	1-14st	1-37st	1-35st	1-75st	1-35st	1-75st	1-24st	1-100st	-	5-30st	1-60st	50 x 3st	-	-	
	LED Extend 50	1-4st	1-4st	1-4st	1-4st	-	-	-	-	-	-	-	-	1st		1-3st	1-7st	1-18st	1-17st	1-37st	1-17st	1-37st	1-12st	1-50st	-	3-15st	1-30st	25 x 3st	-	-	
	LED Extend 75	1-3st	1-3st	1-3st	1-3st	-	-	-	-	-	-	-	-	1st		1-2st	1-15st	1-12st	1-11st	1-25st	1-11st	1-25st	1-8st	1-33st	-	2-10st	1-20st	16 x 3st	-	-	
	Duralight LED 24V	0,4-8m	0,4-8m	0,4-6m	0,4-8m	-	-	-	-	-	-	-	0,4-3m		0,4-5,5m	0,4-11m	0,4-29m	0,4-27m	0,4-60m	0,4-27m	0,4-60m	0,4-19m	0,4-80m	-	1-19m	0,4-48m	40 m x3st	-	-		
	Thin Panel	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-	1st	1st	1-3st	1st	1-3st	1st	1-4st	-	1st	1-2st	1-2 st x3st	-	-	
	LEDstrip RX 12W/M	0,1-1,5m	0,1-1,5m	0,1-1,4m	0,1-1,5m	-	-	-	-	-	-	-	0,1-0,6m		0,1-1,2m	0,1-2,4m	0,1-6m	0,1-5m	0,1-12m	0,1-5m	0,1-12m	0,1-4m	0,1-16m	-	0,2-4m	0,1-10m	0,1-8 m x3st	-	-		
	LEDstrip RXW 4.8W/M	0,1-4m	0,1-4m	0,1-3,5m	0,1-4m	-	-	-	-	-	-	-	0,1-1,75m		0,1-3m	0,1-6m	0,1-10m	0,1-10m	0,1-10m	0,1-10m	0,1-10m	0,1-10m	10m	10m	-	10m	10m	10 m x3st	-	-	
LEDstrip RXI 30W/M	-	-	-	-	-	-	-	-	-	-	-	-		-	0,035-1m	0,035-2,5m	0,035-2,3m	0,035-5m	0,035-2,3m	0,035-5m	0,035-1,6m	0,035-3m	-	0,035-2m	0,035-4m	0,035-3 m x3st	-	-			
LEDstrip RX RGB 12,5W/M	-	-	-	-	-	-	-	-	-	-	-	-		0,1-1,1m	0,1-2,2m	0,1-6m	0,1-5,5m	0,1-12m	0,1-5,5m	12m	-	-	-	-	-	-	-	0,1-12m	0,1-8 m x3st		

Obs! Samtliga installationer ska följa våra rekommendationer av ledningslängder.